

ELECTRICAL LEGEND											
A		LIGHT FIXTURE DESIGNATION, FLOODLIGHT, SEE LIGHTING FIXTURE									
		LIGHT FIXTURE DESIGNATION, SEE LIGHTING FIXTURE SCHEDULE									
		LIGHTING FIXTURE, SURFACE MOUNTED									
		LIGHTING FIXTURE, RECESSED MOUNTED									
		LIGHTING FIXTURE, WALL MOUNTED									
		1 X 1 FLUORESCENT LIGHT FIXTURE									
\$		TOGGLE SWITCH 120/277V, 20 AMP., (M.H. = 48" A.F.F.), 3-WAY									
\$		TOGGLE SWITCH 120/277V, 20 AMP., (M.H. = 48" A.F.F.), 4-WAY									
\$		TOGGLE SWITCH 120/277V, 20 AMP., (M.H. = 48" A.F.F.)									
\$		TOGGLE SWITCH 120/277V, 20 AMP., KEYSWITCH (M.H. = 48" A.F.F.)									
\$		FAN SWITCH 120/277V, 20 AMP. (HORSEPOWER RATED) (M.H. = 48" A.F.F.)									
\$		DOOR JAM SWITCH (DOOR ACTIVATED) 120/277V, 20 AMP., (M.H. = 48" A.F.F.)									
\$		TOGGLE SWITCH 120/277V, 20 AMP., WITH (M.H. = 48" A.F.F.)									
\$		10 MIN. TIME DELAY, RELAY BY MECH. CONT. INSTALLED BY E.C.									
\$		FAN AND LIGHTING SWITCH 120/277V, 20 AMP. (M.H. = 48" A.F.F.), 3-WAY									
\$		TOGGLE SWITCH 120/277V, 20 AMP., WITH PILOT LIGHT (M.H. = 48" A.F.F.)									
\$		TOGGLE SWITCH 120/277V, 20 AMP., EXPLOSION-PROOF									
\$		SPEED SWITCH 120/277V, 20 AMP. U.O.C. (M.H. = 48" A.F.F.)									
\$		SINGLE PHASE MANUAL MOTOR STARTER, (M.H. = 48" A.F.F.)									
\$		DIMMER SWITCH 120/277V, 20 AMP., (M.H. = 48" A.F.F.)									
		DUPLEX RECEPTACLE, 20 AMP., 125V., (M.H. = 48" A.F.F.)									
		DUPLEX RECEPTACLE, 20 AMP., 125V., RECESS FLOOR MOUNTED									
		DUPLEX RECEPTACLE, 20 AMP., 125V., CEILING MOUNTING.									
		USB OUTLET, (M.H. = 18" A.F.F.)									
		DUPLEX RECEPTACLE, 20 AMP., 125V., TOP HALF SWITCHED, (M.H. = 18" A.F.F. UNLESS OTHERWISE NOTED)									
		DUPLEX RECEPTACLE, 20 AMP., 125V., ISOLATED QND. AND SURGE PROTECTED, (M.H. = 18" A.F.F.)									
		SINGLE RECEPTACLE, 20 AMP., 125V., COORDINATE M.H. WITH DEDICATED EQUIPMENT									
		FOUR-PLY QUAD RECEPTACLE, 20A., 125V., (M.H. = 48" A.F.F.)									
		SPECIAL PURPOSE OUTLET 220V 3/4" RANGE OUTLET, COORD. W/ EQUIP.									
		DUPLEX RECEPTACLE, 20 AMP., 125V., MOUNT ABOVE COUNTER									
		30 AMP., 125V., TWIST LOCK RECEPTACLE FOR FLOOR POLISHING MACHINE									
		JUNCTION BOX, MOUNTING AS SHOWN									
		GARAGE DOOR PUSH BUTTON SWITCH									
		ELECTRIC MOTOR									
		MOTOR STARTER									
		COMBINATION MOTOR STARTER, TYPE AS DESIGNATED									
		ELECTRICAL PANEL, SEE PANEL SCHEDULE SHEET(S) FOR DETAILS									
		EXISTING EQUIPMENT TO REMAIN									
		NEW EQUIPMENT OR WORK OF THIS PROJECT									
		SMOKE ALARM/CO SENSOR COMBINATION									
		120V WITH BATTERY BACK UP									
		CIRCUIT BREAKER, TYPE AND SIZE AS PER DRAWINGS.									
		LOW VOLTAGE LIGHTING KEYPAD									
		CLOCK									
		BELL									
		TELEPHONE PORT FLOOR MOUNTED									
		DUAL TELEPHONE OUTLET MOUNTED AT 18" A.F.F. USE CAT-5 W/1" STUD UP 6" ABOVE CEILING.									
		DUAL TELEPHONE OUTLET MOUNTED AT 54" A.F.F. USE CAT-5 W/1" STUD UP 6" ABOVE CEILING.									
		COMPUTER/DATA/TELEPHONE OUTLET MOUNTED AT 18" A.F.F. USE CAT-5 W/1" STUD UP 6" ABOVE CEILING.									
		TELEVISION OUTLET (M.H. = 18" A.F.F.)									
		LIGHTING TRANSFORMER									
<table border="1"> <thead> <tr> <th colspan="4">ABBREVIATIONS</th> </tr> </thead> <tbody> <tr> <td>A.C.</td> <td>ABOVE COUNTER</td> <td>G.F.I.</td> <td>GROUND FAULT INTERRUPTER</td> </</tr></tbody></table>				ABBREVIATIONS				A.C.	ABOVE COUNTER	G.F.I.	GROUND FAULT INTERRUPTER
ABBREVIATIONS											
A.C.	ABOVE COUNTER	G.F.I.	GROUND FAULT INTERRUPTER								

ELECTRICAL GENERAL NOTES

1. IT SHALL BE UNDERSTOOD THAT ALL WORK PERFORMED SHALL BE BY A LICENSED ELECTRICAL CONTRACTOR IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE, CONTRACTOR SHALL MEET ALL REQUIREMENTS SET FORTH BY ANY LOCAL ORDINANCE AND GOVERNING AUTHORITIES.

2. EXISTING INSTALLATION SHALL BE IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE, LATEST EDITION NEC 2017 AND THE LATEST EDITIONS OF ALL LOCAL CODES, RULES 2022, AND ORDINANCES HASVING JURISDICTION FEB 2022., 7TH EDITION.

3. IT SHALL BE THE RESPONSIBILITY OF THE ELECTRICAL CONTRACTOR TO PROVIDE ALL LABOR, MATERIALS, AND SUPPLIES NECESSARY TO ACCOMPLISH THE WORK SHOWN AND/OR NOTED ON THE DRAWINGS AND SPECIFICATIONS.

4. ALL REQUIRED INSURANCE SHALL BE PROVIDED FOR PROTECTION AGAINST PUBLIC LIABILITY AND PROPERTY DAMAGE FOR THE DURATION OF THE WORK.

5. ELECTRICAL CONTRACTOR SHALL VISIT THE JOB SITE PRIOR TO BID AND VERIFY ALL CONDITIONS, LOCATIONS, DIMENSIONS AND COUNTS AS SHOWN AND/OR NOTED ON THE DRAWINGS. THIS SHALL INCLUDE ANY AND ALL PARABATIONS REQUIRED PRIOR TO INSTALLATION.

6. IT SHALL BE THE RESPONSIBILITY OF THE ELECTRICAL CONTRACTOR FOR THE ADVANCED GUARANTEE OF LONG LEAD ITEMS SO AS NOT TO INTERFERE WITH THE PROGRESS OF OTHER TRADES OR TO BE IN ANY FORM OR LAG TIME.

7. CONTRACTOR SHALL QUANTIFY ALL MATERIALS AND WORKMANSHIP FREE FROM DEFECTS FOR A PERIOD OF NOT LESS THAN (1) YEAR FROM DATE OF ACCEPTANCE, UNLESS OTHERWISE SPECIFIED OTHERWISE.

8. CORRECTION OF ANY DEFECTS SHALL BE COMPLETED WITHOUT ADDITIONAL CHARGE AND SHALL REPLACE OR REPAIR OF ANY OTHER PHASE OF THE INSTALLATION UNLESS ANY HAVE BEEN CORRECTED PREVIOUSLY.

9. THE ELECTRICAL CONTRACTOR SHALL BE RESPONSIBLE TO REPAIR TO ORIGINAL CONDITIONS ANY AND ALL DAMAGES TO BUILDING'S STRUCTURES, EQUIPMENT AND FURNISHINGS CAUSED DURING PERFORMANCE OF WORK.

10. ALL ELECTRICAL EQUIPMENT, DEVICES, WIRE, ETC. SHALL BE LISTED FOR THE INTENDED USE, WITH UNDERWRITER'S LABORATORIES, INC. (UL) WHERE STANDARDS HAVE BEEN DEVELOPED. THE CONTRACTOR SHALL BE EXPECTED TO FURNISH AND INSTALL ALL ITEMS FOR A COMPLETE ELECTRICAL SYSTEM AND PROVIDE ALL REQUIREMENTS NECESSARY FOR EQUIPMENT TO BE PLACED IN PROPER WORKING ORDER.

11. ALL CONDUIT RUNS ARE SHOWN DIAGRAMMATICALLY. EXACT ROUTING SHALL BE DETERMINED ON THE FIELD, UNLESS OTHERWISE NOTED. THE CONTRACTOR SHALL PROVIDE AND INSTALL THE PROPER NUMBER OF CONDUITS IN ALL RUNWAYS AS REQUIRED TO ACCOMPLISH THE PROPER FUNCTIONING OF THE DEVICE OR EQUIPMENT AS SHOWN.

12. ELECTRICAL CONTRACTOR SHALL BE RESPONSIBLE TO PROVIDE ALL NECESSARY ELECTRICAL PLANS AND ELEVATIONS FOR EXACT LOCATIONS OF ALL EQUIPMENT UNLESS OTHERWISE NOTED.

13. ALL ELECTRICAL CONTRACTOR SHALL KEEP ALL AREAS IN WHICH WORK IS BEING PERFORMED, FREE FROM OBSTALS AT ALL TIMES AND SAID AREAS SHALL BE LEFT BROOM CLEAN AT THE END OF EACH WORKING DAY.

14. CONTRACTOR SHALL PAY FOR PERMITS, FEES, INSPECTIONS, AND TESTING.

15. ARCHITECTURAL AND/OR ENGINEERING EXPENSES THAT ARE INCURRED DUE TO REVISIONS OR SUBSTITUTIONS REQUESTED BY THE CONTRACTOR SHALL BE PAID FOR BY THAT CONTRACTOR.

16. COORDINATE ALL ELECTRICAL SITE WORK WITH GENERAL CONTRACTOR PRIOR TO INSTALLATION.

17. FOR ELECTRIC POWER SYSTEM:

A. COORDINATE POWER SYSTEM WITH POWER COMPANY.

B. VERIFY LOCATION OF POWER SERVICE TERMINATION WITH POWER COMPANY PRIOR TO SCHEDULING BID.

18. FOR TELEPHONE CONNECTIONS:

A. PROVIDE GROUNDING FOR ALL TELEPHONE OUTLETS AND EQUIPMENT PER REQUIREMENTS OF TELEPHONE COMPANY.

B. TELEPHONE CONDUITS SHALL NOT BE INSTALLED IN THE SAME TRUNK WITH POWER AND LIGHTING CONDUITS.

C. TELEPHONE CONDUITS SHALL BE INSTALLED IN THE SAME TRUNK WITH POWER AND LIGHTING CONDUITS.

D. VERIFY LOCATION OF TELEPHONE SERVICE WITH TELEPHONE COMPANY, PRIOR TO SUBMITTING BID.

19. USE EXTERIOR GRADE 3/4" PLYWOOD BACKSPOARDS FOR MOUNTING TELEPHONE EQUIPMENT AND TERMINAL STRIPS. PAINT BOTH ON ALL SIDES AND EDGES WITH TWO COATS OF FLAT BLACK ASPHALT PAINT.

20. ALL CONDUITS SHALL BE IN CONDUITS. ALL CONDUITS SHALL BE GALVANIZED RIGID TYPE (RIGS) EXCEPT: (A) PVC CONDUITS SHALL BE USED UNDERGROUND PROVIDED ELBOWS AND RISERS ARE THERE, WHERE SUBJECT TO PHYSICAL DAMAGE. (B) ELECTRICAL METALLIC TUBING (EMT) MAY BE USED IN CONCRETE WALLS OR CEILINGS WHERE NOT SUBJECT TO EXCESSIVE DAMAGE, DAMP OR CORROSIVE CONDITIONS. (C) LIQUID TIGHT FLEXIBLE CONDUIT WHERE REQUIRED. (D) FLEXIBLE METALLIC CONDUIT (MC CABLE W/ROUNDING CONDUITS), WHERE REQUIRED. (E) FLEXIBLE CONDUITS SHALL BE USED IN CONCRETE WALLS OR CEILINGS WHERE NOT SUBJECT TO EXCESSIVE DAMAGE OR ARE NOT UNDER PAVED AREAS, THEY MAY BE SCHEDULED 40 RIGS, BUT ALL CONDUITS SHALL BE RIGS. RIGS CONDUITS SHALL EXCEED A MINIMUM OF 18 BELOW GRADE.

21. APPLY BITUMASTIC COATING TO ALL METALLIC CONDUITS IN SLABS OR UNDERGROUND.

22. ALL CONDUCTORS SHALL BE COPPER (CU), TYPE THHN OR THXL INSULATION, RATED 90C, 75C OR 60C EXCEPT WHERE NOTED OTHERWISE. TYPE THHN OR THXL INSULATION, RATED 90C, 75C OR 60C EXCEPT WHERE NOTED OTHERWISE. MINIMUM WIRE SIZE SHALL BE #14 AWG INCLUDING CONDUIT, WIRING.

23. WIRE WAYS SHALL BE SIZED AS REQUIRED, PER NEC, UNLESS OTHERWISE NOTED.

24. ALL ELECTRICAL EQUIPMENT SHALL BE RAINWATER NEAR (4) WHERE EXPOSED TO THE WEATHER. ALL EQUIPMENT SHALL BE PROTECTED FROM LIQUID DAMAGE.

25. OUTLET BOXES SHALL BE PRESSED STEEL IN DRY LOCATIONS, CAST ALLOY WITH THREADED RISERS IN WET OR DAMP LOCATIONS AND SPECIAL ENCLOSURE FOR OTHER CLASSIFIED AREAS. ALL CONDUITS IN HAZARDOUS AREAS PER NEC SHALL BE PROPER COORDINATION BETWEEN ELECTRICAL SUBCONTRACTOR AND GENERAL CONTRACTOR FOR PLASTER RING INITIATION WILL BE REQUIRED. NO "GOLF" RINGS SHALL BE ALLOWED. ALL CONDUITS SHALL BE RIGS. RIGS CONDUITS SHALL EXCEED A MINIMUM OF 18 BELOW GRADE.

26. ALL FASE PLATES SHALL BE WHITE DURELESS UNLESS OTHER WIRE INDICATED IN THE DRAWING.

27. MOTOR STATERS SHALL BE MANUAL OR MAGNETIC, AS INDICATED OR REQUIRED, WITH OVERLOAD PROTECTION FOR EACH PHASE. ALL MOTOR SHALL BE EQUIPPED WITH DISCONNECT MOTOR STARTERS.

28. FURNISH AND INSTALL DISCONNECT SWITCHES AND WIRING FOR AIR CONDITIONING EQUIPMENT PER MANUFACTURER RECOMMENDATIONS. CONTROLS SHALL BE PROVIDED BY THE ELECTRICAL CONTRACTOR. ALL DISCONNECT SWITCHES SHALL BE RATED FOR THE EQUIPMENT PROVIDED PRIOR TO INSTALLATION.

29. DISCONNECT SWITCHES SHALL BE SIZED PER NEC TO ACCOMMODATE EQUIPMENT SERVED. DISCONNECT SWITCHES IN 100V DISCONNECT SWITCHES SHALL BE HORIZONTAL RATED, HEAVY-DUTY TYPE.

30. FUSES SHALL BE CURRENT LIMITING, PER UL, RATED 600 VOLTS, UNLESS OTHERWISE NOTED.

31. A. NONMTE FUSED FUSES IN MAIN SWITCHES AND SWITCHES FEEDING PANELS. B. TIME DELAY FUSES FOR MAIN AND A/C CIRCUITS.

32. CIRCUIT BREAKERS SHALL BE BUILT-ON (U.O.), INVERSE-TIME TYPE (THERMAL-MAGNETIC) TWO AND THREE-POLE CIRCUIT BREAKERS SHALL HAVE COMMON TRIP. ALL PANELBOARDS SHALL HAVE COPPER BUS BARS.

33. UNLESS NOTED AS EXISTING, ALL EQUIPMENT, WIRING, DEVICES, ETC. SHALL BE NEW.

34. WHERE CORE DRILLING OF FLOORS/WALLS IS REQUIRED, CONTRACTOR SHALL SEAL OPENINGS WATERIGHT AFTER UTILIZATION. CORES INCLUDING, SHALL BE CORED Holes SHALL BE COORDINATE WITH LOCATION OF EQUIPMENT IN A MANNER, TO BE CLEAN AND FUNCTIONAL. THE CONTRACTOR SHALL INSTALL ONLY ONE CONDUIT PER HOLE AND SEAL THE OPENING AROUND CONDUIT AS SPECIFIED.

35. PROVIDE FIRE RETARANT UL90 APPROVAL SEALANT ON ALL PENETRATIONS OF FIRE RATED PARTITIONS, WALLS AND STRUCTURAL SLABS. IT SHALL BE THE RESPONSIBILITY OF THE ELECTRICAL CONTRACTOR TO VERIFY THE LOCATION OF ALL FIRE RATED LOCATIONS OF ALL SUCH FIRE RATED PARTITIONS, WALLS, AND STRUCTURAL SLABS.

36. BALLASTS SHALL HAVE MIN. POWER FACTOR OF 90%. BALLASTS FOR METAL HALIDE AND HIGH BAY SHALL BE INSTALLED WITH CONSTANT VOLTAGE TYPE WITH 58 WATT LAMPS FOR 108 NOMINAL LINE VOLTAGE VARIATION.

37. THE EQUIPMENT GROUNDING TERMINAL BARS OF THE NORMAL AND ELECTRICAL ELECTRICAL TERMINAL BARS SERVING THE SAME BUILDING SHALL BE BONDING TOGETHER WITH AN INSULATED, CONTINUOUS, COPPER CONDUCTOR NOT SMALLER THAN NUMBER 6.

38. PROVIDE LAMPS WITH EXISTING, SEE LUMINAIRE SCHEDULE FOR LAMP TYPE. CONTRACTOR SHALL VERIFY SIZE OF LAMP AND PROVIDE PROPER HOUSING.

39. ALL CONNECTIONS TO GROUND RIGS & BUILDING STEEL SHALL BE MADE WITH UL APPROVED WELDED CONNECTIONS, UNLESS NOTED OTHERWISE, THE CONTRACTOR SHALL FURNISH AROUNDING CONDUITS FOR ALL CONNECTIONS.

40. PROVIDE MOUNTING BACKSPOARDS FOR ELECTRICAL AND COMMUNICATION EQUIPMENT. BACKSPOARDS SHALL BE OF TYPE "AC" PLYWOOD, PAINTED ON BOTH SIDES AND EDGES WITH TWO COATS OF FLAT BLACK PAINT.

41. PROVIDE A FUSE HOLDER AND FUSE IN THE PRIMARY SIDE OF EACH UNDERGROUND CONDUIT FOR EACH BALLAST (BUSMAN HUB AND FNG OR EQUAL), AT THE HAND HOLE OF EACH EXTERIOR CONDUIT. PROVIDE A FUSE HOLDER AND FUSE IN EACH GROUND MOUNTED EXTERIOR FIXTURES.

42. PROVIDE TELEPHONY ELECTRICAL SERVICE FOR USE BY ALL TRADES DURING CONSTRUCTION AND REMAIN IN PLACE AT COMPLETION OF PROJECT.

43. THE ELECTRICAL CONTRACTOR SHALL FURNISH A COMPLETE SET OF AS-BUILT DRAWINGS, SHOWING ALL CHANGES AND DEVIATIONS TO THE ARCHITECT/ENGINEER PRIOR TO COMPLETION OF THE PROJECT.

44. PREPARE AND ATTY A TYPED DIRECTORY TO THE INSIDE COVER OF EACH PANELBOARD INDICATING LOADS SERVED BY EACH CIRCUIT AND PANEL FEEDING THE BOARD.

45. PROVIDE UL LISTED CONDUIT APPLIED TO BACK "BACK TO BACK" BOXES IN RATED WALLS WHERE THE BOXES ARE LESS THAN 24 INCHES APART MEASURED HORIZONTALLY.

46. NOT USED.

47. METER CANS, HUBS, & LUGS FOR SAME AREA TO BE FURNISHED & INSTALLED BY CONTRACTOR. CONTRACTOR TO VERIFY SPECIFIC TYPE OF METER CAN TO BE USED WITH F.P.L. PRIOR TO BID. ALL THREE PHASE METER AND COMMERCIAL USE METER SHALL HAVE LEVEL BY PER F.P.L. REQUIREMENTS.

48. PROVIDE A PERMANENT STOP SIGN AT COMPLETION OF WORK DOOR TO THE BUILDING THAT THE SERVICE DISCONNECTS ARE LOCATED INSIDE.

49. SLABS SHALL BE PLACED AT THE MAIN DISCONNECT EQUIPMENT INDICATING TYPE AND LOCATION OF ON-SITE DISCONNECTS.

50. C. VOLTAGE AND SERVICE NUMBER SHALL BE INDICATED AT EACH DISCONNECT.

51. NOT USED.

52. THE CONTRACTOR SHALL SUBMIT 6 COPIES OF EQUIPMENT SHOP DRAWINGS FOR ELECTRICAL EQUIPMENT TO THE ENGINEER FOR REVIEW PRIOR TO ORDERING SUCH EQUIPMENT.

53. ELECTRICAL SYSTEM COMPLIANCE WITH FSC ENERGY CONSERVATION CODE:

A. CONTRACTOR SHALL WITHIN 30 DAYS OF SYSTEM ACCEPTANCE PROVIDE RECORD DRAWINGS TO THE OWNER.

B. CONTRACTOR SHALL PROVIDE TO THE BUILDING OWNER OPERATOR MANUAL, AS PART OF THE SYSTEM ACCEPTANCE.

C. THE MAXIMUM VOLTAGE DROP FOR FEEDER SHALL NOT EXCEED 2%.

D. THE MAXIMUM VOLTAGE DROP FOR BRANCH CIRCUITS SHALL NOT EXCEED 3%.

E. CONTRACTOR SHALL PROVIDE A MEANS OF SPACE LIGHTING CONTROL FOR ALL SPACES OCCUPYED BY A MINIMUM HEIGHT PARTICULATE FILTER OR EQUIVALENT TO A MAXIMUM OF 10% OF ALL OCCUPYED LEAVING THE SPACE.

54. F. CONTRACTOR SHALL PROVIDE FOR ALL OTHER SPACES, EACH CIRCUIT DEVICES SHALL BE ACTIVATED EITHER MANUALLY BY AN OCCUPANT OR AUTOMATICALLY AN OCCUPANT. EACH CIRCUIT DEVICES SHALL CONTROL A MAXIMUM OF 2500 SQ FT AND BE CAPABLE OF OVERRIDING ANY TIME OF DAY SCHEDULE SHUT OFF CONTROL FOR MORE THAN 4 HOURS.

55. ALL EMPTY CONDUITS SHALL BE PROVIDED WITH PULL STRING MARKS AT BOTH ENDS.

56. CONTRACTOR SHALL PROVIDE NEUTRAL TO ALL EQUIPMENT UN.

57. DOORS AND GATES CONTROL SHALL BE FURNISHED AND INSTALLED BY CONTRACTOR.

58. PROVIDE TAMPER RESISTANT RECEPTACLES IN DWELLING UNITS AS REQUIRED BY NEC 408.12.

59. CONTRACTOR SHALL PROVIDE A-FACE PROTECTION TO ALL OUTLET LOCATED AT KITCHENS, FAMILLY ROOMS, DINING ROOMS, LIVING ROOMS, PARLORS, LIBRARIES, BEDS, BEDROOMS, SUNROOMS, RECREATION ROOMS, CLOSETS, BATHS, JANUARY AREAS AND OTHER AREAS WHERE THERE IS A MAXIMUM OF 10% OF ALL OCCUPYED LEAVING THE SPACE.

60. ELECTRICAL CONTRACTOR IS RESPONSIBLE TO VERIFY AVAILABLE FLAT CURRENT WITH UTILITY COMPANY PRIOR TO EQUIPMENT ORDERING.

61. NATURAL ILLUMINATION SHALL BE CONTROLLED VIA TIME SWITCH AND PHOTOCELL UL90 PROVIDE ASTRONOMICAL TIME SWITCH CAPABLE OF RETAINING PROGRAMMING AND THE TIME SETTING DURING LOSS OF POWER FOR A PERIOD OF AT LEAST 10 HOURS, AS PER FLORIDA BUILDING CODE EC 405.4.5.4.

62. ON DWELLING UNITS WHEN MORE THAN 12 SMOKE ALARMS ARE TO BE CONNECTED TOGETHER, CONTRACTOR SHALL PROVIDE LOW VOLTAGE HOUSEHOLD FIRE ALARM SYSTEM AS PER NFPA72 SECTION 24.2.2.

63. EXTERIOR LIGHT FIXTURES EXPOSED TO WEATHER, SHALL BE WEATHER PROOF.

64. POLE AS NOTED ON PLAN

65. FUSE AS NOTED ON PLAN

66. FUSE AS NOTED ON PLAN

67. FUSE AS NOTED ON PLAN

68. FUSE AS NOTED ON PLAN

69. FUSE AS NOTED ON PLAN

70. FUSE AS NOTED ON PLAN

71. FUSE AS NOTED ON PLAN

72. FUSE AS NOTED ON PLAN

73. FUSE AS NOTED ON PLAN

74. FUSE AS NOTED ON PLAN

75. FUSE AS NOTED ON PLAN

76. FUSE AS NOTED ON PLAN

77. FUSE AS NOTED ON PLAN

78. FUSE AS NOTED ON PLAN

79. FUSE AS NOTED ON PLAN

80. FUSE AS NOTED ON PLAN

81. FUSE AS NOTED ON PLAN

82. FUSE AS NOTED ON PLAN

83. FUSE AS NOTED ON PLAN

84.

